
Digital Audio Broadcasting

Mike Brookes

SC5 - b

Jan 2006

2

Digital Audio Broadcasting

- DAB Broadcasting
 - OFDM, SFN, Transmission frames
 - UK ensembles, System Parameters
- Source Coding – MP2
- Channel Coding
 - Convolution, Puncturing, Freq & Time interleaving
- Receiver front end
- Channel decoding
- Synchronization

Jan 2006

3

Main References

1. ETSI. "Radio Broadcasting Systems; Digital Audio Broadcasting (DAB) to mobile, portable and fixed receivers". EN 300 401, European Telecommunications Standards Institute, April 2000.
2. W. Hoeg and Thomas Lauterbach. "Digital Audio Broadcasting: Principles and Applications of Digital Radio". John Wiley, 2003.
3. C. Gandy. "DAB: an introduction to the Eureka DAB System and a guide to how it works". Technical Report WHP-061, British Broadcasting Corp, June 2003.
4. M. Bolle, D. Clawin, K. Gieske, F. Hofmann, T. Mlasko, M.J. Ruf, and G. Spreitz. "The receiver engine chip-set for digital audio broadcasting". In Intl Symp on Signals Systems and Electronics, pages 338–342, October 1998.
5. K. Taura, M. Tsujishita, M. Takeda, H. Kato, M. Ishida, and Y. Ishida. "A digital audio broadcasting (DAB) receiver". IEEE Trans Consumer Electronics, 42(3):322–327, August 1996.

Jan 2006

4

History of DAB



- 1986 – DAB consortium formed
 - France, Germany, Netherlands, UK
 - Eureka 147 development project
- 1990 – First trial broadcasts
- 1993 – Public demonstration system in UK
- 1995 – Network broadcasts in UK
- 1997 – World DAB forum formed



Jan 2006 5

Problems with AM and FM

- Multipath fading
 - Reflections from aircraft, vehicles, buildings
 - very large variations in signal strength over distances of ~1 m





- Interference
 - from equipment, vehicles and other radio stations

Jan 2006 6

OFDM

- Orthogonal Frequency Division Multiplexing
- 1536 carriers at 1 kHz spacing
 - symbol length: $0.246 + 1.0 = 1.246$ ms
 - 2 bits per carrier per symbol (DQPSK)



Jan 2006 7

Cyclic Prefix

- Convolution with channel impulse response
 - = sum of delayed, scaled copies

- If channel impulse response < 0.246 ms:
 - No inter-symbol interference
 - DFT gives input spectrum of symbol multiplied by channel response:
 - frequency dependent amplitude and phase shift

Jan 2006 8

Frequency Domain Orthogonality

- Taking DFT of 1 ms segment is equal to
 1. convolving spectrum with sinc (FT of 1 ms window)
 2. sampling at multiples of 1 kHz
- Component frequencies are orthogonal and do not interfere.
- Doppler spread damages orthogonality:


$$\text{ICI power} \approx 0.5 \left(\frac{vf_0 T}{c} \right)^2 P_0 = -14 \text{ dB at } 190 \text{ km/h}$$

Jan 2006

9

Single Frequency Network

- All transmitters send an identical signal
- Interference-free if delay + multipath < 0.246 ms relative to nearest transmitter
- Optimal spacing $\approx c \times 0.246 \text{ ms} = 74 \text{ km}$




- Transmitters further than $\approx 1.2 c \times 0.246 \text{ ms}$ do more harm than good

Jan 2006

10

Fill-in transmitter

- Can have a low-power fill-in transmitter to solve a local reception problem
- Add delay to synchronize with main Tx



Jan 2006 11

UK DAB Multiplexes/Ensembles

BBC: 12B (225.648 MHz)



Digital1: 11D (222.064 MHz)

- Each DAB multiplex: 1.536 MHz bandwidth
 - 0.176 MHz gap between multiplexes
- Four multiplexes per 7 MHz TV channel
 - 2 National ensembles
 - Regional + Local (3 for London)

Jan 2006 12

Spectral Efficiency

- Existing FM transmissions
 - Each transmitter has a bandwidth of 0.2 MHz
 - Nearby transmitters must be 0.4 MHz apart
 - 2.2 MHz needed for a network covering entire country
- DAB
 - 1.5 MHz for 10 services covering entire country using a single frequency network
 - **15 times more efficient !**



Jan 2006

15

System Parameters

- Centre frequency, $f_0 \approx 220$ MHz (Band III)
 - Wavelength > 1 m \Rightarrow diffraction around objects
 - Lower frequencies are full up
- Total bandwidth = 1.537 MHz
 - Needs to be > 1.5 MHz for fading to be frequency selective
 - < 1.6 MHz to fit four into a 7 MHz TV channel
- Cyclic Prefix = 0.246 ms
 - Needs to be $>$ (transmitter spacing)/ $1.2c$ to allow SFN
 - Wasteful if long compared to useful symbol length
- Carrier Spacing = 1 kHz \Leftrightarrow Useful symbol length = 1 ms
 - Symbol length $< 0.4/(\text{Doppler spread}) \approx 0.4c/(f_0v) = 10$ ms
 - Symbol length $<$ cyclic prefix for efficiency
- Transmission frame = 76 symbols = 96 ms
 - Long for efficiency, short for ease of synchronization

Jan 2006

16

Source Coding

- Based on MP2 (MPEG 1 Layer 2)
 - Simpler than MP3 but less good
- Masking – Psycho-acoustic model
 - loud sounds make quieter sounds inaudible at nearby frequencies and times
- Sub-band Processing
 - Input @ 48 kHz sample rate
 - Divide into 32 subbands of 750 Hz @ 1.5 kHz
 - 36 samples/subband in each 24 ms CIF frame
 - Only low 27 subbands are used (0 to 20.25 kHz)

Jan 2006 17

Masking

The graph plots SPL - sound pressure level (db) on the y-axis (0 to 60) against Frequency (kHz) on the x-axis (0.02 to 20). Curve A is the normal hearing threshold. Curve B is a higher threshold caused by tone C at 1 kHz. Band D is a region where the threshold is raised significantly above the normal level.



- Normal hearing threshold is A
- Threshold is changed to B because of tone C
- Higher quantization noise allowed in bands near tone C
- Band D can be completely eliminated
- Threshold calculated from FFT spectrum + Psycho-Acoustic model

Jan 2006 18

Subband Processing

The diagram shows a flow from input to 32 parallel paths, each with a bandpass filter, a 32-sample decimation filter, and an encode block. These are combined in a multiplex block. The signal then passes through a demultiplex block, followed by 32 parallel paths with a 32-sample interpolation filter and a decode block. Finally, the outputs are summed at a central adder (+) and passed through another set of bandpass filters.

- Sample Rates: Input @ 48 kHz, Subbands @ 1.5 kHz
 - Total number of samples stays the same
- Noise and speech spectra are roughly flat within a sideband
- All bandpass filters are 750 Hz wide
 - efficient to implement



Jan 2006

21

Bit Allocation Procedure


- Aim: Maximize the minimum (over all subbands) mask – to - quantization noise ratio
 - If this ratio is > 1 then quantization noise inaudible
- Method
 1. Initialize bit allocation to 0 for each subband
 2. Find the worst subband
 3. Give it an extra bit (or fraction of a bit)
 4. Go back to step 2.
 5. Stop when all available bits are used up

Jan 2006

22

Channel Coding

- Energy Dispersal randomizes carrier phases
- Convolution Code adds protection
- Time interleaving combats burst errors
- Freq interleaving combats freq selective fading
- Inverse DFT converts phases into a waveform



Jan 2006 23

Energy Dispersal

- If carrier phase changes linearly with frequency then IDFT gives a single impulse
 - Bad news for the transmitter
- Solution:
 - XOR data bits with a pseudo-random sequence
 - Generator polynomial: $P(X)=X^9+X^5+1$
 - Reset shift register at start of each 24 ms frame

9-bit shift register + two XNOR gates

Jan 2006 24

Convolution Coding

- Four separate convolution codes with constraint length of 7
 - M bits $\rightarrow 4(M+6)$ bits
- Mother code has rate $\frac{1}{4}$
- Extra 6 bits from emptying the shift register
- Reset Shift-Reg every 24 ms

Output: $x_{0,1} x_{1,1} x_{2,1} x_{3,1} x_{0,2} x_{1,2} \dots x_{3,M+5} x_{0,M+6} x_{1,M+6} x_{2,M+6} x_{3,M+6}$

Jan 2006 25

Puncturing

- Not all $4M+6$ bits are transmitted
- Predefined puncturing patterns. **Examples:**
 - Rate 1/3 code
 - 8 input bits \rightarrow 32 mother \rightarrow 24 transmitted
 - Transmit: \checkmark
 - Rate 2/3 code
 - 8 input bits \rightarrow 32 mother \rightarrow 12 transmitted
 - Transmit: \checkmark
- Code for each service defined in FIC
 - FIC itself always uses rate 1/3 code

Jan 2006 26

Unequal Error Protection

- Some audio code bits are much more critical than others
 - e.g. **bit allocation**, **scale factors**, **samples**, **text**
- Predefined unequal protection rates
- **Example: 128kbps UEP level 3**

$3072 \text{ bits} / 24 \text{ ms} = 128 \text{ kbps}$

$6040 \text{ bits} / 24 \text{ ms} (0.51)$

Jan 2006 27

Time Interleaving

← 6040 bits / 24 ms →

0	8	4	12	2	10	6	14	1	9	5	13	3	11	7	15	0	8		
---	---	---	----	---	----	---	----	---	---	---	----	---	----	---	----	---	---	--	--

- Makes data robust to burst errors
- Delay each bit by between 0 and 15 CIF frames
 - Delay between 0 and 360 ms
 - Imposes a coding delay of at least 360 ms
 - Requires memory in the receiver
- Delays of adjacent bits differ by $\geq 4 \times 24$ ms
 - Adjacent bits are always in different transmission frames
- Not used for Fast Information Channel

Jan 2006 28

Frequency Interleaving

← 2 sync + 75 data symbols = 96 ms →

data for one symbol = 3072 bits

1536 carriers (excluding 0 Hz)

-768 kHz 0 +768 kHz


- The first 1536 bits of the symbol are assigned to carriers in a pseudo random sequence (same for all symbols).
- The next 1536 bits use the same sequence.
- Each carrier gets 2 bits (0 Hz carrier is not used)
- Prevents fading causing burst errors

Jan 2006
29

DQPSK Modulation

- If $x_k, y_k \in \{0,1\}$ are the bits that map onto carrier k , then the complex amplitude for symbol n of a transmission frame is:


$$a_k(n) = a_k(n-1) \times (1 - 2x_k + (1 - 2y_k)j) / \sqrt{2}$$




- All carriers have constant $|a_k(n)|=1$
- Called $\frac{1}{4}\pi$ DQPSK because phase increment is an odd multiple of $\frac{1}{4}\pi$
- Worst case discontinuity at symbol boundary is 1.71 (instead of 2 for plain DQPSK without the $\frac{1}{4}\pi$)



Jan 2006
30

Transmitter Output

— = complex


- 1537 carriers padded with zeros to 2048 for efficient IFFT
- cyclic prefix added to complex IFFT output
- Real/Imag parts modulate $\cos(\omega t)$ and $\sin(\omega t)$
- Bandpass filtered to remove sidelobes
 - -71 dB bandwidth = 1.94 MHz
- DC carrier unused – difficult to control phase





Jan 2006 33

Downsampling

- Analog filter removes images at 12 MHz spacing
- Digital sampling @ 24 MHz \Rightarrow 30 MHz aliased to 6 MHz
- Complex digital filter removes images at 2 MHz spacing
 - negative frequencies removed completely
 - use polyphase filter and combine with downsampling
- Downsample to 2 MHz \Rightarrow 6 MHz aliased to DC

Jan 2006 34

Receiver Demodulation


- Time-sync selects a 1 ms window for the FFT
- Freq-sync multiplies complex signal by $e^{j\omega_{\text{offset}}t}$ to correct for tuning errors and doppler shifts
- CORDIC block calculates phase and amplitude for DQPSK demodulation

Jan 2006

35

Channel Decoding

- Must reverse the channel coding:




- FFT (and later processing) need only process symbols that contain the wanted service
- Time de-interleaving requires time delays of up to 15 CIF frames (24 ms each) – needs memory

Jan 2006

36

Viterbi Decoding

- Mother code is $\frac{1}{4}$ rate
 - Punctured before transmission
- Receiver must unpuncture to restore original mother code but with “unknown” bits
- Constraint length of 7 \Rightarrow trellis has $2^6 = 64$ states
- Branch metric compares input 4 bit sequence with “correct” value:
 - Cost for each bit = -1 if correct, +1 if wrong, 0 if punctured
- Delay decisions for ≈ 32 bits
- Re-encode and compare with input to estimate BER



See Data Comms lecture 19

Jan 2006

37

Soft Decisions

- "hard decision" decoder uses branch metric of ± 1
- Ideal Branch metric is $\log(\text{prob}(z | x))$
 - z is observed bit, x is "correct" bit
 - adding and/or multiplying by a constant makes no difference
- Can calculate ideal metric if you know the noise characteristics:
 - Flat Rayleigh fading with complex FFT output s_n
 - Ideal branch metrics for the two QPSK bits are


$$\pm \Re(s_n s_{n-1}^*) \text{ and } \pm \Im(s_n s_{n-1}^*)$$
 - Use a 4-bit signed number to represent this

Jan 2006

38

Error Concealment

- Errors in MP2 bit allocation bits or high bits of scale factors are catastrophic
 - CRC check words are included in the MP2 bit stream
 - If these are wrong then sound is muted




Jan 2006

41

Effect of Frequency Offsets

- FFT samples spectrum at multiples of 1 kHz
- If carrier frequencies have an offset, Δ_f , then they will no longer be orthogonal
 - must measure Δ_f and compensate
 - compensation can be combined with the FFT
- Divide Δ_f into integer and fractional multiple of 1 kHz
 - Integer part \Rightarrow wrong carriers
 - Fractional part \Rightarrow inter carrier interference



Jan 2006

42

Fine AFC




- Frequency error of $\Delta_f \Rightarrow$ additional phase shift between successive symbols of $\Delta\phi = 2\pi\Delta_f T$
 - T is symbol period = 1.246 ms
- Phase shift for each carrier should be $(\frac{1}{4} + \frac{1}{2}k)\pi$ in the absence of noise
 - Find deviation from nearest correct value
 - Form energy-weighted average of phase error over all carriers
 - calculate Δ_f
 - apply correction before or during FFT calculation by multiplying input signal by $\exp(-2\pi j\Delta_f t)$
- Only works to within a multiple of $\frac{1}{4}\pi$

Jan 2006

43

Coarse AFC

- Transmitted phases of phase reference symbol carriers are known:
 - Subtract transmitted phases from FFT output and do inverse FFT
 - Try lots of values of Δ_f in the range ± 8 kHz or so
 - Subtract phases due to Δ_f
 - Result is impulse response of channel
 - Pick Δ_f that gives the highest peak
 - Position of peak indicates where to put the end of the cyclic prefix



Jan 2006

44

Benefits of DAB

- CD quality
- Mobile reception
- Spectral Efficiency
- European Standardisation
- Data as well as Audio
- Lower transmitter power
- Receiver features
 - easy tuning
 - pause